



[Knowledgebase](#) > [Moto Watch 100](#) > [Troubleshooting & Setup](#) > [Customizing Your Motowatch 100 Screen Timeout](#)

Customizing Your Motowatch 100 Screen Timeout

Inas B. - 2025-10-08 - [Troubleshooting & Setup](#)

The Screen Timeout feature helps save battery by turning off the display after a period of inactivity. Follow these steps to adjust it:

1. Press the Top Button

- Access the main menu by pressing the top button on your Motowatch 100.

2. Go to Settings

- Navigate to **Settings** to open watch configuration options.

3. Select Display

- Choose **Display** to access screen-related settings.

4. Access Screen Timeout

- In Display settings, tap **Screen Timeout**.

5. Set Your Preferred Duration

- Select your desired interval (in seconds) for the screen to automatically turn off.

Adjusting the Screen Timeout helps balance battery conservation with screen visibility.